doric

Wireless Fiber Photometry

User Manual

Version 1.0.0

Contents

1	System Overview 1.1 Wireless Fiber Photometry System	3 3
2	Specifications	9
3	Appendix	11
4	Support 4.1 Maintenance 4.2 Warranty 4.3 Contact us	15 15 15 15

System Overview

1.1 Wireless Fiber Photometry System

The Wireless Photometry System (Fig. 1.1 & 1.2) is a cable-free solution to acquire neuronal data without restricting the animal movement. The Wireless Headstage integrates both LED light sources and detectors to excite and collect photometry signals between the *fiber optic Cannula* and the *Console*.

A standard Wireless Fiber Photometry system (Fig. 1.1 & 1.2) contains the following elements:

- The Wireless Fiber Photometry Headstage. See section 1.1.1.
- The Wireless Base-Station. See section 1.1.2.
- The Headstage Battery Charger. See section 1.1.3.
- The Dummy Headstage. See section 1.1.4.
- The Fiber optic cannula.
- The Neuroscience Console 500 (NC500) or Behavior and Bundle Photometry Console 300 (BBC300). The table below compares the main features of both consoles.
- The Doric Neuroscience Studio software.

	BBC300	NC500
SUPPORTING		
# base station per console	4	2
# headstage per base-station	1	4
Max # headstages per console	4	8
COMPATIBILITY		
Wireless Photometry	Х	Х
Basic Photometry		Х
Bundle Photometry	Х	Х
Miniature Microscopy		Х
Electrophysiology		Х

Table 1.1:	Comparing	consoles	for wireless	photometry



Figure 1.1: Wireless Fiber Photometry System with NC500



Figure 1.2: Wireless Fiber Photometry System with BBC300

1.1.1 Wireless Fiber Photometry Headstage



Figure 1.3: Headstage and disabeler

The Wireless Headstage (Fig. 1.3) is an optic-electronic device that creates the link between the fiber optic cannula and the base-station. It contains LED drivers, two LEDs of choice (isosbestic + biosensor excitation), and a detector to both send light pulses for illuminating the fluorophores and collect the emission wavelengths. The headstage also uses a battery to power the LEDs.

- The Antenna (Fig. 1.3) is a small ridge on the side of the headstage used to transmit wireless photometry signal.
- The **Battery** is the source of power for the headstage to function. It can support around two hours of recording at the highest power of the LEDs. Once the battery is assembled to the headstage, it is ideal to not disconnect it in order to increase the longevity of the device. In fact, more than 20 disconnect-reconnect cycles can significantly loosen the connector on the headstage. Once the experiment is finished, to save the remaining power of the battery, the headstage should be connected to the battery charger base or the Disabeler (Fig. 1.3). Otherwise, the headstage will continue to search for wireless connections and use the battery.

* Upon customer request, it is possible to replace the battery with a larger one for long-term recordings. The larger batteries are more appropriate for recordings in rats.

- The **Headstage connector** (Fig. 1.3), found on the underside of the headstage, links it to the 2.5 mm ferrule cannula via a small screw.
- The **Docking Port** (Fig. 1.3) is used by the *Headstage Charger* to recharge the headstage battery, as well as reprogramming it if necessary.
- The **Disabeler** (Fig. 1.3) is used to disable the wireless connection to reduce battery degradation when the headstage is not used.

1.1.2 Wireless Photometry Base-Station



The *Base-station* (Fig. 1.4) transmits the information among the headstage and the photometry console (NC500 and BBC300).

On the front view (Fig. 1.4a), the base-station contains the following:

- The Antenna communicates with the headstage at 2.4 GHz. The range is up to 2 m distance.
- The On/Off LED light displays whether the base-station is on and functioning.
- The 1-4 LED lights display three different colors each indicating:
 - **Blue**: The headstage is paired with the base-station but not enabled in the Doric Neuroscience Studio (DNS) software.
 - **Green**: The headstage is both paired with the base-station and enabled in the Doric Neuroscience Studio (DNS) software.
 - All 4 LEDs blinking green: The base station has been correctly initiated. This will happen for a short period of time at power up (This apply for the NC500 and may change for BBC300).
 - **LEDs 3 and 4 blinking white**: The headstage is on the bootloader mode, which means the firmware can be reprogrammed.

On the back-side view (Fig. 1.4b), the base-station contains two ports:

- The **USB** port is a USB-B input through which the firmware of the base-station channels can be updated. Besides, it can also connect the *Base-station* to the Doric BBC300 console.
- The **DATA** HDMI connector is used to connect the base-station to the NC500 console. Connect the base station to one of two possible *Ephys* HDMI ports.

If the base station is NOT recognized by the computer, refer to the Appendix (Chapter 3) for additional troubleshooting information.

1.1.3 Wireless Headstage Charger





The Wireless Headstage Charger (Fig. 1.5) is used to recharge the headstage battery and shut down the wireless connection. During the pairing process, all unused headstages must be docked on the charger, otherwise they will be detected in-place of the target headstage.

- The **USB-C Connector** behind the *Wireless Headstage Charger* is used to connect it to the console or directly to a computer to supply the power to charge the headstages. When the charger this connected to a power source, the *Status Lights* on top of the *Wireless Headstage Charger* will turn on.
- The four **Docking Ports** are used to recharge up to 4 headstages at a time. When a headstage is connected to a docking Port, its wireless connection is shut down to reduce battery degradation.
- The **Status LED Lights**, on the side of each charging port, displays the connection stage of the headstages.
 - The **Orange** light means no headstage is connected.
 - The Green light means the headstage battery is fully charged.
 - The **Red** light means the headstage is connected and charging.
- The **P-O** key across the docking port 1 is a switch that allows users to update the firmware of the headstage. It should always be in "O" for charging purposes. However, if a firmware update of the headstage is required, this key should be on "P" side. In this condition (the small LED light of port one will turn to white color), only one headstage which is connected to the docking port 1, can be updated, and it will automatically appear in the Doric Maintenance Tool software.
- The **Antenna Position Indicator** shows the proper placement of the antenna when docking a headstage to recharge the battery.

1.1.4 Dummy Headstage

The Dummy Headstage is a simplified version of the Wireless Headstage that is used to habituate an animal subject to the weight of the headstage. It contains no electronics or other valuable components, and will not function as a Wireless Headstage.

Specifications

SPECIFICATIONS	VALUE	NOTES
Dimensions	Height 29.38 mm	
	VVidth 19.24 mm	
	INICKNESS 15.29 mm	
Mass	4.55 g	Including 40 mAh battery
	2.95 g	Without battery
Transmission Frequency	2.4 to 2.5 GHz	
RF Data Speed	2 Mbps	
Sampling Rate	10 kHz	On each channel
ADC Resolution	14 bits	
Saturation level	~6 nW	
Detector Bandwidth	0 - 500 Hz	
Roll-off rate for low-pass filter	-40 dB/decade	
Detector Sensitivity	~0.48 V / nW	@ 520 nm
Operation distance	0-2 m	For optimal performance
Maximum LED Power	405 / 415 nm = 100 μW	With 400 μ m fibre
	470 nm = 150 μW	
	560 nm = 20 μW	

Table 2.1: Wireless Headstage General Specifications

Table 2.2: Wireless Fiber Photometry Base-Station Specifications

SPECIFICATIONS	VALUE	NOTES
Dimensions	Height 28.50 mm Width 108 mm Thickness 87 mm	Without antenna
Antenna dimension	Length 108.5 mm Diameter 9 mm	
Mass	230 g	
Transmission Range	Up to 2 m	
Wireless Frequency Band	2.4 - 2.5 GHz	
Number of Headstage	Up to 4	With NC500 console
	1	With BBC300 console
Base Station Interface	HDMI	With NC500 console
	USB-B	With BBC300 console

SPECIFICATIONS	VALUE	NOTES
Dimonsions	Hoight 81 mm	
Dimensions	Width 63.47 mm	
	Thickness 17.07 mm	
Mass	170 g	
Charger Interface	USB-C	
Charger Power Supply	AC/DC adapter 5 Watt (5 V, 1 A)	With 1 meter cable USB-C to USB-A
Charger Headstage Capacity	4	
Battery charge duration	120 min	With 2 LEDs at 100% power
Battery recharge time	~60min	For a 40 mAh battery

Table 2.3: Wireless Fiber Photometry Battery Charger Specifications

Appendix

When using the **BBC300** console with a Base-station on a new computer for the first time, it is very likely that the Base-station will **NOT** be recognized properly by the computer.

Below are the instructions to install the correct driver for the Base-station to ensure proper functionality.

1. Verify that the device is correctly connected by ensuring the white LED next to the SMA connector remains steadily illuminated (Figure 3.1).



Figure 3.1: The white LED on the Base-Station indicating that the device is powered on.

- 2. On the computer, access the **Device Manager** by typing its name in the Windows search bar and selecting it from the results (Figure 3.2).
- 3. Check if Wireless Base-station appears under the Other devices tab with an exclamation mark (Figure 3.3).
 - If it appears with an exclamation mark, proceed with updating the USB driver.
 - If it does not appear, the issue is not related to the USB driver update.
- 4. Open Zadig. This software is installed as part of the Doric Neuroscience Studio installation. By default, it can be found in: C:\Program Files\Doric Lenses\Doric Neuroscience Studio\drivers\utils under the name zadig-2.5.exe.
- 5. Select Wireless Base-station from the dropdown menu (see label 1 in Figure 3.4).
- 6. Click on Install Driver (see label 2 in Figure 3.4).



Figure 3.2: Find the Device Manager by Windows search bar.

7. Once the installation is complete, confirm that *Wireless Base-station* appears under the *Universal Serial Bus devices* tab in Device Manager (Figure 3.5).



Figure 3.3: Missing USB driver for Wireless Base-station in Device Manager.

🖾 Zadig	- 🗆 X
Device Options Help	
Wireless Basestation 1	✓ [] Edit
Driver (NONE) → WinUSB (v6.1.7600.16385) → USB ID 1915 C0D3 Install Driver 2 →	More Information <u>WinUSB (libusb)</u> <u>libusb-win32</u> <u>libusbK</u> <u>WinUSB (Microsoft)</u>
1 device found.	Zadig 2.5.730

Figure 3.4: USB driver installer for Wireless Base-station.



Figure 3.5: Wireless Base-station displayed in Device Manager after successful USB driver installation.

4

Support

4.1 Maintenance

The product does not require any maintenance. Do not open the enclosure. Contact Doric Lenses for return instructions if the unit does not work properly and needs to be repaired.

4.2 Warranty

This product is under warranty for a period of 12 months. Contact Doric Lenses for return instructions. This warranty will not be applicable if the unit is damaged or needs to be repaired as a result of improper use or operation outside the conditions stated in this manual. For more information, see our Website.

4.3 Contact us

For any questions or comments, do not hesitate to contact us by:

Phone 1-418-877-5600

Email sales@doriclenses.com



© 2025 DORIC LENSES INC

357 rue Franquet - Quebec, (Quebec) G1P 4N7, Canada Phone: 1-418-877-5600 - Fax: 1-418-877-1008 www.doriclenses.com